

# CHARGER

SRMK.BATTERY CHARGER WH-SERIES TYPE



Full size chargers/boosters designed especially for outdoor service shop, farm and garage high power boosting to turn over stubborn engine. Activating dry and dead battery, maintenance free and conventional battery. Mounted on a 2-wheels cart with a handy push handle for complete mobility. All models feature variable charging rate control for multiple charging rates from slow charging, high charging to boosting.

เครื่องชาร์จแบตเตอรี่ SRMK. ประเภท WH เหมาะสำหรับงานสนาม, โรงรถ, ไร่, ช่อมรถ, โรงซ่อม โรงฝึกงาน ทุกรุ่นจะมีปุ่มปรับกระแสจากชาร์จช้าไปจนถึงชาร์จเร็ว และช่วยสตาร์ทรถยนต์ จึงสามารถชาร์จได้กับแบตเตอรี่ทุกขนาด, แบตเตอรี่แบบไม่ต้องเติมน้ำกลั่น แบตเตอรี่แผ่นด้านที่ไม่ได้ชาร์จมานาน

## Feature

- NORMAL CHARGE ,FAST CHARGE ,BOOSTER (สวิตช์เลือก ชาร์จช้า ,เร็ว , ช่วยสตาร์ทอัติโนมัติ)
- FULL WAVE SILICON RECTIFIER (ไดโอดต่อแบบเต็มคลื่น)
- AUTOMATIC REVERSE POLARLITY PROTECTION SOUND BUZZER&LED (วงจรป้องกันการกลับขั้วอัติโนมัติ)
- SIMULATE BUTTON (ปุ่มกระตุ้นแบตเตอรี่ตาย)
- AMP METER AND VOLT METER (ติดตั้งแอมป์ และ โวลท์มิเตอร์ ดี ซี)
- BOOST POWER TO SPIN ENGINE (สามารถช่วยสตาร์ทรถยนต์)
- AUTOMATIC CIRCUIT BREAKER TO PREVENT OVERLOAD (ใช้เบรกเกอร์ป้องกันการลัดวงจร)
- 3 HOURS TIMER CONTROL ;FAN COOLING (นาฬิกาตั้งเวลา 3 ชั่วโมง ; พัดลมระบายความร้อน)

## SPECIFICATION

MODEL	OUTPUT VOLTAGE	DISCHARGE RATING	BOOSTER CRANKING POWER	CHARGING CORDS	DIMENSION(inch) DEEP WIDE HIGN	WEIGHT Kgs
WH1240	6-12 V	40A for6V-40Afor12V	200 A	305Cm.(10ft)	12" 12" 23"	-
WH1260	6-12 V	60A for6V-60Afor12V	300 A	305Cm.(10ft)	12" 12" 23"	-
WH2100	6-12 V	100A for6V-80Afor12V	500 A	305Cm.(10ft)	14" 12 3/4" 24"	-
WH2440	6-12-24 V	40A for6,12V-30Afor24V	200 A	305Cm.(10ft)	14" 12 3/4" 24"	35
WH2460	6-12-24 V	60A for6,12V-50Afor24V	300 A	305Cm.(10ft)	14" 12 3/4" 24"	39
WH24100	6-12-24 V	100A for6,12V-80Afor24V	500 A	305Cm.(10ft)	14" 12 3/4" 24"	45